

## SRNE BATTERY COMPATIBLE INVERTER LIST (LOW VOLTAGE BATTERY)

### V1.1

Brand	Model No.	RS485/ CAN	RJ45 Pin Definition	Protocol Selection
	SR-HESP48120(100/80)S(U)200-H SR-HESP4860(50/40)S(U)100-H SR-ASP48100(80)S(U)200-H SR-ASF48120SH3 SR-HYP4850S(U)100-H SR-HF4835U60-H/SR-HF4850U80-H SR-HFP4850S80-145/SR-HFP4850S80-H	RS485	7:RS485-A 8:RS485-B	SRNE(WOW)
		CAN	4:CAN-H 5:CAN-L	SRNE(WOW)
	SUN-3/3.6/5/6K-SG04LP1-EU SUN-3.6/5/6K-SG03LP1-EU SUN-3.6/5/6/7.6/8KSG05LP1-EU SUN-5/6K-SG01LP1-US SUN-7.6/8K-SG01LP1-US/EU SUN-5/6/8/10/12KSG04LP3-EU SUN-12/14/16K-SG01LP1-EU	RS485	1:RS485-B 2:RS485-A 7:RS485-A 8:RS485-B	Deye
		CAN	4:CAN-H 5:CAN-L	Deye
	SPF3500ES SPF5000ES SPF6000ES SPH3000/3600/4000/4600/5000/6000	RS485	RS485-B:1 RS485-A:2	Growatt
		CAN	4:CAN-H 5:CAN-L	Growatt
	Infini Solar V IV TWIN 6/6.5/8kw Axpert VM III Axpert VM IV Axpert MKS III Axpert MKS IV Axpert MAX Axpert MAX II	RS485	3:RS485-B 5:RS485-A	Voltronic
	SUNSYNK-3.6/5/8K-SG01LP1 SYNK-8/10/12K-SG04LP3 SUNSYNK MAX	CAN	4:CAN-H 5:CAN-L	Deye/Pylon
	SOL-ARK 5K-1P-N SOL-ARK 5K-2P-N SOL-ARK 8K-2P-N SOL-ARK 12K-2P-N SOL-ARK 15K-2P-N	CAN	4:CAN-H 5:CAN-L	Deye/Pylon

	S6-EH1P(3-6)K-L-EU S6-EH1P8K-L-PRO	CAN	4:CAN-H 5:CAN-L	Solis
	GW3000-ES-20 GW3600-ES-20 GW5000-ES-20 GW6000-ES-20	CAN	4:CAN-H 5:CAN-L	GOODWE
	R8KLNA R7K6LNA R6KLNA R5KLNA	CAN	4:CAN-H 5:CAN-L	Megarevo
	AF(3-6)K-SL	CAN	4:CAN-H 5:CAN-L	Afore
	SNA 3000W/4000W/5000W/6000W LXP3000W/LXP6000W LXP-LB-EU 8K/10K SNA US 6000 LXP-LB-US 12K	CAN	4:CAN-H 5:CAN-L	Luxpower
	XD3KTL/XD3K6TL/XD5KTL/XD6KTL	CAN	4:CAN-H 5:CAN-L	INVT
	PV1800 VM PV1800 VHM	RS485	1:RS485-B 2:RS485-A	Paceic
	H1-3K-S2 H1-3.6K-S2 H1-4K-S2 H1-4.6K-S2 H1-5K-S2 H1-6K-S2	CAN	4:CAN-H 5:CAN-L	Pylon

to be continued...